
House amplifiers
High power amplifiers

- built-in adjustable gain & slope regulators
- interstage discrete attenuator and equalizer
- switchable passive or active return path
- input attenuator for active return path
- test points: input - bi-directional, output - directional
- die-cast housing

HA224, HA225
without return path

HA224R65, HA225R65, HA226R65
with return path 65 MHz

HA226R85
with return path 85 MHz



Technical specifications

TYPE	HA224	HA224R65	HA225	HA225R65	HA226R65	HA226R85
Ordering number	10587	10588	10592	10593	10594	10595
Forward path						
Frequency range	47-862 MHz	87-862 MHz	47-1006 MHz	87-1006 MHz	87-1218 MHz	108-1218 MHz
Gain	42 dB					
Gain adjustment	18 dB					
Slope adjustment	18 dB					
Interstage attenuator	-10/-5/0 dB					
Interstage equalizer	-10/-5/0 dB					
Flatness*	±0.75 dB					
Input and output return loss	≥ 14 dB at 40 MHz; -1.5 dB/oct., but not less 10 dB					
Output level CTB, CSO (EN60728-3)**	114 dBμV					
Noise figure	6 dB					
Test points***	-20 dB					
Return path						
Frequency range	-	5-65 MHz	-	5-65 MHz		5-85 MHz
Gain, switchable	-	27/-5 dB	-	27/-5 dB		
Gain adjustment	-	18 dB	-	18 dB		
Input attenuator	-	-10/0 dB	-	-10/0 dB		
Output equalizer	-	-6/-3/0 dB	-	-6/-3/0 dB		
Flatness	-	±0.75 dB	-	±0.75 dB		
Return loss	-	> 14 dB	-	> 14 dB		
Noise figure	-	7 dB (active, 0 dB input attenuator)	-	7 dB (active, 0 dB input attenuator)		
Output level IMD3=60 dB (EN60728-3)	-	114 dBμV (active) 121 dBμV (passive)	-	114 dBμV (active), 121 dBμV (passive)		
General						
Power consumption	230 V~ 50/60 Hz 12 W	230 V~ 50/60 Hz 13.5 W	230 V~ 50/60 Hz 12 W	230 V~ 50/60 Hz 13.5 W		
Operating temperature range	-20° ÷ +50° C					
Dimensions/Weight (packed)	185x91x47 mm/0.7 kg					

* for amplifiers with return path measured 10 MHz after the starting frequency of forward path

** with 5 dB interstage equalizer

*** input test point is bi-directional and could be used as return path output test point; output test point is directional and could be used for insertion return path signals

